



Petrol Generator Model IG6000

Alternator Specifications

Rated Frequency (Hz)	50
Rated Voltage (V)	230
Rated Current (A)	24
Rated Speed (rpm)	3600
Rated Output (kVA)	5.5
Maximum Output (kVA)	6
DC (12v) Voltage (Battery Charging Facility)	12 Volt - 8.3A
AC (230v) Plug Outlets	Two
Phase Number	Single phase

Petrol Engine Specifications

Model	KG390Gi
Type	Single Cylinder: four stroke, vertical, air cooled, OHV, petrol engine
Displacement (L) (cc)	389cc (88 x 64mm)
Rated Power (kW /rpm)	7.7 / 3600
Ignition System	T.C.I
Smart Throttle (Power on Demand)	Yes
Choke for easy starting	Yes
Spark Plug	F6RTC
Starting System	12 Volt Electric Starter
Fuel	Automotive Unleaded Petrol
Lube Oil	SAE10W30
Low oil pressure alert/shut down system	Yes
Low fuel cut out protection	Yes

General Specifications

Fuel Tank Capacity (L)	22
Continuous Running time (Hr) (Rated Output)	7.5
Noise Level (dBA @ 7m)	62 - 64
Dimensions: unpacked (L x W x H)	700*500*640 (mm)
Dimensions: Packed (L x W x H)	720*530*670 (mm)
Dry Weight Unpacked / Packed (Kg)	95 / 115 (Kg)
Wheels and Handles	Yes
ISO9001 & CE certified	Yes